

Gasoline Generator
6500W

RH-4783

- 420 cc, 4-Stroke 8600w engine with considerable performance
- 25 Liter full steel fuel tank provides up to 7 hours of run time
- Special compact design for ease of use and better portability
- Circuit breaker outlets for added protection
- Minimum sound and vibration in indoor usage
- 100% copper-wound generator head allows continuous operation without overheating
- Includes one (12V) DC outlets
- Ideal for workshops and light-duty industrial usage



Model	RH-4783		
Generator	Type	Gasoline Generator	
	AC Voltage	220V	
	Rated Amperage	27A	
	Frequency	50Hz	
	Max. Output	6.5KW	
	Rated Output	6KW	
	Power Factor	1	
	DC Output	DC 12V, 8.3A	
	Engine	Model	FC190F
		Type	Single Cylinder, 4-Stroke, Forced Air Cooled
BorexStroke		90mmx66mm	
Displacement		420cc	
Max. Output		8.6KW / 3600RPM	
Fuel		Gasoline	
Fuel Tank Capacity		25 Lit	
Rated Continuous Operation		7 hr	
Lubricating Oil		SAE 10W-30	
Lubricating Oil Capacity		1.1 Liter	
Starting System		Recoil & E-start	
Ignition System		T.C.I	
Spark Plug: Type	F7TC/F7RTC		

Engine	Maximum Fuel Consumption Rate	3.57 Lit/hr
Dimension	Net Dimension LxWxH	686x516x560mm
	Overall Dimension LxWxH	740x575x625mm
	Net Weight	83Kg
	Gross Weight	85Kg
Supplied in	Carton	
Include	2 Plug, 1 Spark Plug Sleeve, 1 Rod, 12V DC Output Clip, 2 Key, 1 Set Wheels And Handles	